



#### Notes:

- 0/ A classic Golden Ratio for Markaudio CHN-110
- 1/ All panels 18mm except for the vent spacer
- 2/ Vents are 15mm high, vent spacer is 132mm wide and centrally located. Different material for the spacer is recommended
- 3/ brace shape is only suggestive – prime purpose is to brace driver, it should touch the magnet but not put any pressure on it. Should be about 35-40% holes. (ie if you have to mount a terminal cup in the middle, you'll want to make sure the brace allows clearance), It is just off-centred
- 4/ Don't forget to angle cut the back of the driver cut-out to give it breathing room
- 5/ All internal panels lined with ~1/2" (12mm) cotton or wool felt (preferred), 3/4" (19mm) poly-fluff batting, or 1" (25mm) fiberglass Note that it is hard to get into the box after it is sealed up (means terminals need to be solderable from outside the box as well)



CGR CHN-Ken110s ov82

Markaudio CHN-110 | plan 18mm  
© 2011-24 planet\_10 enterprises limited  
16-july-2024 | designed & drawn by dld  
free for non-commercial use